

# SILENT 3600W INVERTER GENERATOR - caravan camping fishing



**3.6 KVA**

Electric start & remote control



**BUILT TO LAST!**



**Pure Sine Waves**

Designed for sensitive electronics



**Economical**

14 L = 7 continuous working hours



**Quiet Operation**

59 dB at 4 metres



**Compact & Portable**

Easy to carry

**TECHNICAL SPECIFICATION**

<b>Generator</b>	
Type	Digital Inverter / Sine Wave
Dimension (mm)	625x500x540 (LxWxH)
Net Weight	37 kg
Rated/Max AC Output	3 kW / 3.6 kW
Frequency / Rated voltage	(50/60 Hz) / (240 v)
<b>Engine</b>	
Type	Overhead Valve/Forced-Air Cooling/single Cylinder/4 Stroke Overhead camshaft
Displacement	230 cc
Compression Ratio	8 : 1
Engine Speed	3600 rpm
Fuel Tank Capacity	14 L
Fuel Consumption	360g/kwh
Starting System	Pulling Recoil/Electric/Remote Starting (TDI )
Continuous Working Time	7 hours
Noise Level	59 dB/4m
<b>Standard Features</b>	
AC Overload Protector	Flow pattern
AC Socket	2 x 240 v
<b>Optional Features</b>	
DC Socket (12v/6A)	"T" type
DC Protector	0

**FEATURES:**

- Total Convenience
- Compact & Lightweight
- Super Quiet Operation
- Pure Sine Wave
- Excellent Fuel Consumption